

auto electrical parts

Technical Information Sheet

Part No. 0-727-83


Voltage sensitive relay, 24 volt 140 amp with red LED indicator. Allows split charging of second battery bank without discharging the primary/start battery, relay makes at 27.4 volts and breaks at 25.6 volt. I 68 x w 54 x h 68mm. CE approved.


Additional information


A 5 second delay operates when the voltage falls below the cut-out voltage to prevent nuisance cut-out due to high intermittant loads on the battery. Supplied with self tapping screws and ring crimp terminal for ground lead.



Technical Drawing (not to scale)







Specification

Type
Voltage
Current
Cut-in voltage
Cut-out voltage
Cut-out time delay
Terminals
Ground lead
Dimensions

Voltage Sensitive Relay

24 volt

140 amp maximum 27.4 volt (±0.1 volt) 25.6 volt (±0.1 volt)

5 seconds 2 x M6

600mm

See diagram

220g

The information contained in this document is correct to the best of our knowledge at the time of printing. However, specifications may change at any time without notice.



Weight